

(example programming overlay)






(example set display: change on lower right soft key)

The following lists the step by step process to setting the Time & Date.

**System :** [Norstar 6x16, 8x24 and 0x32 RIs 1-T1](#)

Press: Feature \*\*23646.....Display: Shows **Password**  
 Press: 23646.....Display: Shows **1: Sys speed dial**  
 Press: next until.....Display: Shows **3: Time and Date**  
 Press: show.....Display: Shows **Time 09:00** eg (current time)  
 Press: change.....Display: Shows **Hour:09**  
 Press: change.....Display: Shows **Hour:\_\_\_**  
 Enter hour from dial pad.....Display: Shows **Hour:10** eg

If only changing hour press  to exit programming or press  to continue.  
 .....Display: Shows **Minutes:15** eg  
 Press: change.....Display: Shows **Minutes:\_\_\_**  
 Enter minutes from dial pad..Display: Shows **Minutes:30** eg

Press  .....Display: Shows **AM**  
 Press: change.....to toggle to **PM**

If you are only changing the time and not the date, press  to end your session. Press: next for Date options...

**System :** [Norstar CICS and MICS 2.0 and later.](#)



Press: Feature \*\*8463 (which is the same as Feature \*\*TIME)  
 .....Display: Shows **Password**  
 Press: 22742 (which is the same as BASIC)  
 .....Display: Shows **Hour:09** eg  
 Press: change.....Display: Shows **Hour:\_\_\_**  
 Press the dial pad buttons to enter the hour. Use two digits for all hours. The clock on the display will show either one or two digits.

**Notes:** If entering 24 hour clock format (ie: 16 for 4pm) the following step is not shown.

If entering 12 hour clock format (ie: 04 for 4pm) the following step is required.

Press: change.....Display: Shows **AM**

Press  or press  and  to select **PM**

If only changing hour press  to exit programming or press  to continue.  
 .....Display: Shows **Minutes:15** eg  
 Press: change.....Display: Shows **Minutes:\_\_\_**  
 Enter minutes from dial pad..Display: Shows **Minutes:30** eg

If you are only changing the time and not the date, press  to end your session. Press: next for Date options