



Vernon Telecom Incorporated

4218 Bella Vista Road
Vernon BC V1T 2N4

Tel (250/888) 542-3212
Fax (250) 545-2905
service@vernontelecom.com

Below are the step by step instructions to update the time and date on your Samsung telephone systems. These instructions will work for all systems installed by Vernon Telecom Inc.

Samsung Time and Date change:

- Leave the handset down.
- Press the Transfer button, you will see "PROGRAMMING MODE"
- Dial 200, you will see "ENABLE CUST.PROG."
- Passcode: 12341
- Press SPKR key, you will see "201:CUS.PASSCODE"
- Dial 505
- Then you will see on the first line; OLD: (then the current time and date)
- On the second line you will see NEW: WMMDDYY:HHMM
- Enter the day of the week for W (Monday=1 - Sunday=7)
- Dial digits: Month for MM, Day for DD, Year for YY, military time for HHMM
- Press the transfer button to save, this will update the time on all sets.